

# CoreStore™ MV/MP Firmware Upgrade

## *For the Marvell Controller*

The following procedure was provided by Marvell to update the firmware on the SSD Controller used in the CoreStore MV/MP.

**WARNING** – The following upgrade procedure will reset the drive back to factory condition before your data was introduced. Please backup all data before executing this upgrade procedure.

**Note:** This procedure involves creating a DOS bootable USB flash drive. Please create a DOS bootable flash drive before proceeding. The steps to create a Bootable flash drives maybe found on various locations on the web. Search for “Bootable USB DOS”

### **Instructions:**

1. If you have not already done so, download the Firmware updater, **fw\_upt\_v2037.zip**. You may find it on our website [http://www.supertalent.com/support/driver\\_download.php#](http://www.supertalent.com/support/driver_download.php#)
2. Extract the contents of **fw\_upt\_v2027.zip** and copy to bootable DOS USB
3. To begin the upgrade process, type “**go**” at the command prompt >
4. During the Reboot process, Type **Ctrl-M** to enter the CoreStore BIOS
5. Select **Advanced** and enter
6. Select **Erase Drive**. Enter “**Y**” at the warning message to proceed
7. Select **F10** to Save configuration and reboot